

Instructions:

Lightweight Vertical housing for single or double Sessions



Step 1: Insert the three screws into their sockets at the base of the camera housing.



Step 2: Place the housing on top of the glove, into the plastic cup. Rotate it back and forth until you feel the screws catch on the threaded holes inside the cup.



Step 3: Insert the hex wrench through the small holes to tighten the screws.

Make each screw snug but not tight. The wrench must go straight down through the small holes. Otherwise the housing could be damaged.



Step 4: Wear the glove and rotate the housing to the desired angle.

Then remove the glove and tighten the screws another $\frac{1}{2}$ to $\frac{3}{4}$ turn. Maybe a little more, but the screws don't need to be extremely tight.



Step 5: Each camera must go straight into its socket. If the camera seems stuck, back it out a little and restart.

The bottom camera goes in upside down, while the top camera can be upright or can have its door facing up.




Step 6: Make sure both cameras are fully inserted.

*Sometimes when pressing on the back wall of a Session camera, especially near the back button, the back button will activate. If this happens, just leave it for 5 seconds and the screen will deactivate.



Step 7: Insert the back cover. A slight curve needs to be pressed into the cover as it's inserted.

Slide it all the way up against the top stop, then press each of the two bottom tabs into position until they pop into place.



Step 8: After popping both tabs into place, verify they are secure.

Removal of cameras is a reverse of the previous instructions. Start by pulling up and out on the fabric tab to release the plastic tabs.



WARNING! Funjump Rigging has made every attempt to build their products to be as safe as possible. However Funjump Rigging, their dealers, and employees cannot be held responsible for injuries, losses, or death occurring through proper or improper use of their product. At the moment of use, the user accepts full responsibility for their own well-being and property with full knowledge of the risks involved in their activities.